

§ 129.323

the generator or motor is derated to 80 percent of the full-load rating and if the rating or setting of the overcurrent devices of the generator or motor is reduced accordingly.

(c) For each generator rated at 50 volts or more, a voltmeter and an ammeter used for measuring voltage and current while the generator is in operation must be provided. For each alternating-current generator, a means for measuring frequency must also be provided. To ensure satisfactory operation of each generator, additional control equipment and measuring instruments, if needed, must also be provided.

(d) Each generator must have a nameplate attached to it indicating—

(1) Name of manufacturer, type of generator, and designation of frame;

(2) Output in kilowatts, or horsepower rating;

(3) Kind of rating (continuous, overload, or other);

(4) Amperes at rated load, voltage, and frequency;

(5) Number of phases, if applicable;

(6) Type of windings, if DC;

(7) When intended for connection in a normally grounded configuration, the grounding polarity; and

(8) For a generator derated to comply with paragraph (b)(2) of this section, the derated capacity.

(e) Each motor must have attached to it a nameplate containing the information required by Article 430 of NFPA 70.

§ 129.323 Multiple generators.

If an OSV uses two or more generators to supply electricity for the ship's service loads, to comply with § 129.310(a) of this subpart, the following requirements must be met:

(a) Each generator must have an independent prime mover.

(b) The circuit breaker of a generator to be operated in parallel with another generator must comply with §§ 111.12-11(f), 111.30-19(a), and 111.30-25(d) of this chapter.

(c) The circuit breaker of a generator not to be operated in parallel with another generator must be interlocked to prevent that generator from being connected to the switchboard simultaneously with another.

46 CFR Ch. I (10-1-10 Edition)

§ 129.326 Dual-voltage generators.

If a dual-voltage generator is installed on an OSV—

(a) The neutral of the dual-voltage system must be solidly grounded at the switchboard's neutral bus and be accessible for checking the insulation resistance of the generator; and

(b) Ground detection must be provided that—

(1) For an alternating-current system, complies with § 111.05-27 of this chapter; and

(2) For a direct-current system, complies with § 111.05-29 of this chapter.

§ 129.330 Distribution panels and switchboards.

(a) Each distribution panel or switchboard must be in a location as dry as practicable, accessible, adequately ventilated, and protected from falling debris and dripping or splashing water.

(b) Each distribution panel or switchboard must be totally enclosed and of the dead-front type.

(c) Each switchboard must have nonconductive handrails.

(d) Each switchboard or main distribution panel must be fitted with a dripshield, unless the switchboard or distribution panel is of a type mounted deck-to-overhead and is not subject to falling objects or liquids from above.

(e) Each distribution panel and switchboard accessible from the rear must be constructed to prevent a person's accidental contact with energized parts.

(f) Working space must be provided around each main distribution panel and switchboard of at least 610 millimeters (24 inches) in front of the switchboard and, of at least 460 millimeters (18 inches) from the nearest bulkhead, stiffener, or frame behind the switchboard. Rear access is prohibited when the working space behind the switchboard is less than 460 millimeters (18 inches).

(g) Nonconductive mats or grating must be provided on the deck in front of each switchboard and, if the switchboard is accessible from the rear, on the deck behind the switchboard.

(h) Each uninsulated current-carrying part must be mounted on noncombustible, nonabsorbent, high-dielectric insulating material.